

STUDENT TELEPHONE

USER'S GUIDE

Getting Started	2
Your Telephone Number	
Assistance & Problem Reporting	
Voicemail Service	
Analog Adapters	
Things To Know About Your Telephone Service.....	2
Calling Into the University	
Emergency Service	
Directory Assistance	
Personal Billing Number	
Words of Caution	
User Guide for Telephone Service	2
Function Keys	
Lamps	
Physical Features	3
Microphone On/Off	
Change Hands-Free	
Adjust Initial Receiving Volume - Temporary	
Ringer Tone	
Adjust Transmission/Receiving Volume - Permanent	
Right Corner Call Indicator Lamp On/Off	
Function Features	3
Transfer a Call	
Originating Calls	
Place a Call on Hold	
Establish a Consultation Hold	
Conference Call	
Call Park	
Answer Call Waiting - LED is lit	
Call Forwarding	
Originate a Call Using a One-Touch Button	
Billing Information	4
Blue Light Emergency Telephones & Security	4
Harassment & Discrimination	4

The complete Telephone and Voicemail User's Guide can be found online at:
http://www.utd.rochester.edu/documentation/nec_user_guide.pdf

Getting Started

Your Telephone Number

Welcome to the University of Rochester and the University's digital telephone system.

- Your telephone number is (585) 27x-xxxx, where x-xxxx represents the five-digit extension on your telephone.
- Five-digit extensions are used for dialing other numbers on the telephone system.
- Our web site www.rochester.edu/its/ contains point-and-click instructions on how to use your telephone and voicemail.

Assistance & Problem Reporting

For assistance with your telephone or for questions on placing calls, call ITS/Telecommunications at x44357 (4-HELP) or the ITS Center at x52000.

Voicemail Service

The University maintains a digital voicemail system. The system access and forwarding number is x43660. The default voicemail passcode [**37842556**] needs to be changed as you set up your mailbox. Periodically change your password to ensure that your voice mailbox remains secure. See the "Voicemail System" section for these procedures. Basic mailbox service provides space for four (4) messages. Additional messages are available in groups of five at a monthly rate of \$2.92 per group.

Analog adapters

For a monthly charge of \$6.50, an adapter can be rented to enable the use of analog devices, like a facsimile, with your telephone.

To sign up for voicemail or analog adapter services, visit www.rochester.edu/incoming/.

Things To Know About Your Telephone Service

Calling into the University

When calling a University extension from outside the University use the full 7-digit telephone number: 273-xxxx, 274-xxxx, 275-xxxx, 276-xxxx, 341-xxxx and 506-2000 through 506-9999. 7-xxxx cannot be reached from outside the University.

Emergency Service

- **X13** reaches University Security for emergencies
- **#413** reaches University Security if you have Cingular or Verizon cellular telephone service.
- x53333 reaches University Security for non-emergency questions or issues.
- See Blue Light Emergency Telephones in this section.
- See "Think Safe" at www.security.rochester.edu.

Directory Assistance

University Directory Assistance - Dial 0
(7AM-5:30PM, Monday-Friday)

Operator Assisted Calls - ONLY Collect, Credit Card, Calling Card, or Third Party verified calls can be made. These calls incur a surcharge plus charges for conversation time.

Dial 9 + 0 + telephone number

800/888 Numbers

9+1+ 800/888 telephone number

800/888 information

9+1-800-555-1212

900 Telephone Numbers - are NOT available on the University's telephone system.

A Personal Billing Number (PBN) is required to use these services:

Long Distance:

*3 + PBN + 1 + Area Code + 7-Digit Number

International Long Distance:

*3 + PBN + 011 + Country Code + City Code + Number

Directory Assistance (Long Distance and Local):

*3 + PBN + Area Code + 555-1212

Rate information is available online by logging into your account at campuslink.paetec.com or by contacting PAETEC Customer Service. Rates are subject to change with or without notification. To ensure you have up-to-date rates, periodically check the website.

On the base and handset of your telephone are stickers which provide important telephone numbers for Emergency and Security services as well as the ITS Center. Basic information regarding voicemail operation is included for your convenience.

Words of Caution

Your digital telephone does not work outside of the University's system. Unplugging and moving the telephone to another jack can result in features and/or functionality being lost; **please leave the telephones in their original wall jacks.**

You are responsible for all charges to your Personal Billing Number; keep your code confidential and treat it as you would a credit card.

User Guide for Telephone Services

FUNCTION KEYS

- **UP/DOWN ROCKER** - adjust speaker, receiver, and ringer volume.
- **HOLD** - place a call on hold.
- **TRANSFER** - transfer a call to another telephone.
- **ANSWER** - see and answer a waiting call.
- **SPEAKER** - use the built-in speaker for hands-free dialing or answer.
- **REDIAL** - re-dial the last number dialed; use the * key to initiate call.
- **CONF** (conference) - establish up to an eight-party conversation. The LED on the button lights when active. The transfer button is used to connect the callers.
- **FEATURE** - access various telephone features and to program one-touch speed dial/feature buttons. See Function Features in these procedures.
- **RECALL** - end a call and receive dial tone again, as if you hung up and lifted the receiver.

LAMPS

- MIC Lamp - displays the status of the built-in microphone used for hands-free answer back.
- Right Corner Call Indicator Lamp – flashes for incoming call; steady indicates voicemail.
- Light Emitting Diode (LED) - some function buttons have a built in LED that lights or flashes according to the activity of that function button.

PHYSICAL FEATURES

Microphone On/Off ~ Controls status of built-in microphone for hands-free telephone calls.

To Change Microphone Status:

- Press feature button & the digit "1" on touch-tone pad.

Note: If the microphone is on, this will turn it off. If the microphone is off, this will turn it on. The MIC light will indicate the status of the microphone.

Change Hands-Free ~ Enables user to converse via speakerphone.

To Activate Hands-Free Mode: Press FEATURE [5]

To Cancel Hands-Free Mode: Press FEATURE [6]

Adjust Initial Receiving Volume (Temporary) ~ Enables user to adjust volume in the handset.

Display: Press FEATURE [2]

Volume Adjustment: Press FEATURE [2]

Note: Once the call is completed, the volume reverts to the normal setting.

Ringer Tone ~ select one of four different ringing tones

Ringer Status: Press FEATURE [3]

Adjust Transmission/Receiving Volume (Permanent) ~

Adjusts volume heard through the handset permanently, until the user resets the volume.

Volume Adjustment: Press FEATURE [4]

Right Corner Call Indicator Lamp On/Off ~ User may turn the indicator lamp on/off while ringing; lamp remains on for Message Waiting Lamp.

To View/Change: Press FEATURE [7]

FUNCTION FEATURES

Transfer a Call ~ Move a call from one extension to another extension.

- Ask party to hold.
- Press TRANSFER; receive interrupted dial tone.
- Dial the telephone extension the calling party wishes to be connected to, hang up or wait for answer.

To Retrieve a Transferred Call:

- Before you hang up, press TRANSFER. You will be reconnected to the party.

Originating Calls

To Originate a Call:

- Press SPEAKER or lift handset; receive dial tone.
- For external calls, dial 9 and the desired telephone number.
- For internal calls, dial the 5-digit extension.

Authorization Code Use: You are able to place a long distance call from any phone on the University's telephone system (except pay telephones) by using your Personal Billing Number (PBN). When you use this number, you are authorizing PAETEC Communications to bill you for your long distance and directory service calls.

- For Long Distance:
*3 + PBN +1 + Area Code + 7-Digit Number
- For International Long Distance:
*3 + PBN + 011 + Country Code + Number
- Directory Assistance (Long Distance or Local)
*3 + PBN + Area Code + 555-1212
- See the University of Rochester Calling Guide or look online at campuslink.paetec.com or call PAETEC Customer Service at 1-800-962-4772.

Place a Call on Hold ~ Temporarily hold a call without disconnecting the caller.

- Press HOLD once - held line will flash.

To Retrieve:

- Press SPEAKER or lift handset.
- Press held line

If Unanswered:

- After a preprogrammed time of approximately 2.5 minutes, automatic recall is initiated.
- A visual and audible signal (rapid flashing and ring burst) will be sent to the telephone that placed the call on hold.

Note: Your telephone will show a Flashing Green LED when on hold. Recall will show as a Rapid Flashing Green LED.

Establish a Consultation Hold ~ This feature allows user to consult with a third party while on another call.

- While engaged in a call and wishing to consult a third party, press TRANSFER; caller is automatically placed on hold.
- Dial desired party to consult.
- Re-press transfer to return to original caller. Third party is automatically placed on hold. Repeat these steps to alternate between calls.

Conference Call ~ Allows you to add another party to an existing conversation. Up to eight parties can be included in a conference call.

To Establish a Conference Call:

- With call in progress, ask party to hold.
- Press TRANSFER; receive interrupted dial tone and then dial desired number.
- After call is answered, press CONF; LED lights. Three way conference call is now established.

Note: If one party hangs up, the other two remain Connected. Repeat steps to add more parties; up to eight parties may be included.

Call Park ~ This feature enables the telephone user to park a call that can then be retrieved from another extension.

To Program Call Park Key (on one-touch speed calling button):

- Press FEATURE then press desired one-touch speed button.
- Press RECALL then dial CALL PARK access code (*6) and then press FEATURE.

To Park A Call:

- When on a call press TRANSFER, and dial the CALL PARK access code (*6).

To Retrieve a Parked Call from Originating Telephone:

- Dial the CALL PARK local retrieval code (**6). Parked call is connected to the extension where the call was parked.

To Retrieve a Parked Call from A Remote Station:

- Dial the CALL PARK remote retrieval code (##6) and the extension of the telephone that parked the call.
- Remotely parked call is connected to the extension where the code was dialed.
- Connection to calling party is established.
- If currently on a call, the original party must be placed on hold before new call can be picked up.

Answer Call Waiting - LED is lit ~ The light indicates that another call is waiting. You will hear a tone (internal = one beep; external = two beeps) indicating that there is an incoming call.

- While engaged in a call, receive call waiting indication (one short tone burst).
- Press ANSWER; call in progress is placed on hold.
- Connection to call waiting is established.
- Re-press ANSWER to return to original call; call waiting is placed on hold.
- Repeat these steps to alternate between calls.
- When party has answered, converse, or lift handset.

Call Forwarding ~ All calls destined for a particular extension will be routed to another extension

To Set:

- Press SPEAKER; receive dial tone.
- Press FWD code (*41 for external calls, *40 for internal calls); receive special dial tone.
- Dial destination extension number; receive interrupted dial tone.
- Hang up; call forward is set.

To Cancel:

- Press SPEAKER; receive dial tone.
- Press FWD access code (#41 for external calls, #40 for internal calls); receive dial tone.
- Hang up, call forward is canceled.

Note: If you suspect your calls are being forwarded, cancel all forwarding.

Originate a Call Using a One-Touch Button

- Press SPEAKER or lift handset.
- Press desired SPEED DIAL button.

To Program:

- Press FEATURE button.
- Press desired SPEED DIAL button.
- Enter desired telephone number or feature code on the keypad.
- Press FEATURE button again to save the number.

To Verify:

- Press FEATURE button.
- Press desired SPEED DIAL button.

To Originate a Call:

- Lift handset or press SPEAKER button.
- Press desired SPEED DIAL button.

Note: To program a hookswitch for transfer or feature activation, press RECALL key as first digit. To program a pause, press RECALL button as any digit other than the first digit.

BILLING INFORMATION

For students using the long distance service offered through PAETEC Communications:

Personal Billing Number ~ You are able to place a long distance call from any phone on the University's telephone system (except pay telephones) by using your Personal Billing Number (PBN). When you use this number, you are authorizing PAETEC Communications to bill you for your long distance and directory service calls.

Account Information ~ Visit the PAETEC website, campuslink.paetec.com, to review detailed account information, get answers to frequently asked questions and to review rate information for specific calls. To log onto your account, you will need your PBN and your 11-digit Account ID as printed on your account statement or PBN card. If you need additional instruction on how to view your account, contact PAETEC Customer Service at 1-800-962-4772.

Individualized Billing ~ A monthly invoice will be on the PAETEC website within 10 days after the end of each monthly billing cycle (the 25th day of each month). You may request a paper copy of your statement. A charge of \$1.00 will be assessed for each paper invoice requested. To have your bill mailed or to update your mailing address, call PAETEC Customer Service at 1-800-962-4772.

How to Pay Your Bill ~ Check online at campuslink.paetec.com or call PAETEC Customer Service at 1-800-962-4772.

BE SURE TO PROTECT YOUR CODE AND DO NOT GIVE OUT YOUR LONG DISTANCE ACCESS CODE. PAETEC Communications should be **notified immediately by telephone, and in writing**, if misuse or unauthorized use is suspected.

Keep your account in good standing. If you have any questions about payment or invoicing, contact PAETEC Communications.

BLUE LIGHT EMERGENCY TELEPHONES & SECURITY

Special Blue Light Emergency Telephones are located throughout the University. Information on telephone location and security policies, programs, procedures, hate crimes and crime statistics is published in Think Safe and is available by calling Security at x53340. For more information, look online at www.security.rochester.edu.

Emergency calls to Security can be made from a Cingular or Verizon telephone by dialing #413.

HARASSMENT & DISCRIMINATION

Information on sexual harassment policies and procedures for reporting are published in the brochure Prevention of Harassment and Discrimination which is available by calling the Intercessor's Office at x59125.